

SAMPLE

検査成績表

<TEST REPORT>

品名<Model Name> (デジタルマルチメータ)
<DIGITAL MULTIMETER>
形名<Model Number> (DT4223)
製造番号<Serial No.> (No. 170909574)
検査年月日<Test Date> (2017-09-05)
<YYYY-MM-DD>
検査条件<Test Conditions> (21.7 °C, 63 %rh)

項目 <Item>	ファンクション <Function>	レンジ <Range>	入力 <Input>	許容範囲 <Tolerance>	校正値 *1 <Calibration Value>
確度 <Accuracy>	交流電圧 <AC voltage>	6 V	0.06 V 50Hz	0.052 V ~ 0.068 V	(0.060 V)
			5.4 V 50Hz	5.343 V ~ 5.457 V	(5.400 V)
			5.4 V 50Hz	5.262 V ~ 5.538 V	(5.395 V *2)
			5.4 V 300Hz	5.316 V ~ 5.484 V	(5.400 V *3)
		60 V	0.6 V 50Hz	0.52 V ~ 0.68 V	(0.60 V)
			54 V 50Hz	53.43 V ~ 54.57 V	(54.00 V)
		600 V	6 V 50Hz	5.2 V ~ 6.8 V	(6.0 V)
			540 V 50Hz	534.3 V ~ 545.7 V	(539.9 V)
	直流電圧 <DC voltage>	600 mV	0 mV	-0.5 mV ~ 0.5 mV	(0.0 mV)
			-540 mV	-543.2 mV ~ -536.8 mV	(-539.9 mV)
			540 mV	536.8 mV ~ 543.2 mV	(540.0 mV)
		6 V	0 V	-0.005 V ~ 0.005 V	(0.000 V)
			-5.4 V	-5.432 V ~ -5.368 V	(-5.401 V)
			5.4 V	5.368 V ~ 5.432 V	(5.401 V)
		60 V	0 V	-0.05 V ~ 0.05 V	(0.00 V)
			-54 V	-54.32 V ~ -53.68 V	(-54.00 V)
			54 V	53.68 V ~ 54.32 V	(54.00 V)
		600 V	0 V	-0.5 V ~ 0.5 V	(0.0 V)
			-540 V	-543.2 V ~ -536.8 V	(-540.0 V)
			540 V	536.8 V ~ 543.2 V	(539.9 V)

備考<Note>

*1. FAIL判定箇所は、グレー表示としています。<FAIL decision points are highlighted in gray.>

*2. フィルタON(100Hz) <Filter ON(100Hz)>

*3. フィルタON(500Hz) <Filter ON(500Hz)>

総合判定<Overall Result>	検査者<Inspected By>	承認者<Approved By>
(PASS)	()	()

SAMPLE

検査成績表

<TEST REPORT>

HIOKI
HIOKI E. E. CORPORATION

2/2

製造番号<Serial No.> (No. 170909574)
検査年月日<Test Date> (2017-09-05)
<YYYY-MM-DD>

項目 <Item>	ファンクション <Function>	レンジ <Range>	入力 <Input>	許容範囲 <Tolerance>	校正値 *1 <Calibration Value>
確度 <Accuracy>	周波数 <Frequency>	100 Hz 1000 Hz 10 kHz	90 Hz (0.6V) 900 Hz (6V) 9 kHz (60V)	89.89 Hz ~ 90.11 Hz 898.9 Hz ~ 901.1 Hz 8.989 kHz ~ 9.011 kHz	(90.01 Hz) (900.0 Hz) (9.001 kHz)
	導通 <Continuity>	600 Ω	0 Ω 540 Ω	-0.5 Ω ~ 0.5 Ω 534.1 Ω ~ 545.9 Ω	(0.0 Ω) (540.6 Ω)
	抵抗 <Resistance>	600 Ω 6 kΩ 60 kΩ 600 kΩ 6 MΩ 60 MΩ	0 Ω 540 Ω 0 kΩ 5.4 kΩ 0 kΩ 54 kΩ 0 kΩ 540 kΩ 0 MΩ 3 MΩ 0 MΩ 30 MΩ	-0.5 Ω ~ 0.5 Ω 534.7 Ω ~ 545.3 Ω -0.005 kΩ ~ 0.005 kΩ 5.347 kΩ ~ 5.453 kΩ -0.05 kΩ ~ 0.05 kΩ 53.47 kΩ ~ 54.53 kΩ -0.5 kΩ ~ 0.5 kΩ 534.7 kΩ ~ 545.3 kΩ -0.005 MΩ ~ 0.005 MΩ 2.968 MΩ ~ 3.032 MΩ -0.05 MΩ ~ 0.05 MΩ 29.50 MΩ ~ 30.50 MΩ	(0.1 Ω) (540.3 Ω) (0.001 kΩ) (5.403 kΩ) (0.00 kΩ) (54.03 kΩ) (0.0 kΩ) (540.3 kΩ) (0.000 MΩ) (3.001 MΩ) (0.00 MΩ) (30.04 MΩ)
	AUTO V	600 V	0 V 540 V 540 V	-0.3 V ~ 0.3 V 528.9 V ~ 551.1 V 528.9 V ~ 551.1 V	(DC 0.0 V) (DC 539.9 V) (AC 540.0 V)

項目 <Item>	ファンクション <Function>	入力 <Input>	結果 *1 <Result>
確度 <Accuracy>	検電 <Electric charge>	20 V 50Hz 80 V 50Hz	(検出しない <Not detect>) (検出する <Detect>)
			(PASS) (PASS)